



ALIMENTAZIONE STROMVERSORGUNG/POWER SUPPLY	380-415V 3N~ 50/60Hz
M=MORSETTIERA ANSCHLUSSKLEMME/TERMINAL CLAMP	FV122 6 POLI - 40 A - 450 V
K1, K2=RELE RELAYS/RELAY	FINDER 62.83.8.230.0300 3NO=3mm
B1, B2 = COMMUTATORE SCHALTER/SWITCH	50.55071.100 13A 230V

RF1 = RESISTENZE FORNO SUP. HEIZKÖRPER F. BACKOF./HEATING EL. OVEN	3300 watt 230 V 14.5 A
RF2 = RESISTENZE FORNO INF. HEIZKÖRPER F. BACKOF./HEATING EL. OVEN	2300 watt 220 V 10.5 A
BF = COMMUTATORE FORNO SCHALTER BACKOFEN/OVEN SWITCH	49.44215.700+49.21015.705 0,1,2,3 POS 16A 250V T150
S1 = LIMITATORE DI TEMPERATURA SICHERHEITSTHERM./SAFETY THERM.	EGO 55.32574.110 T=360°C -25K 20(4)A 400V
T1 = TERMOSTATO THERMOSTAT/THERMOSTAT	EGO 55.34052.811 16A 250V T150 [60°C - 295°C]

LR = LAMPADA ROSSA KONTROLLAME ROT/RED IND. LIGHT	SIGNAL LUX Mod 21.3 230V (T120) Silicon Leads
LB = LAMPADA BIANCA KONTROLLAME WEI&WHITE IND. LIGHT	SIGNAL LUX Mod 21.3 230V (T120) Silicon Leads
LV = LAMPADA VERDE KONTROLLAME GRÜN/GREEN IND. LIGHT	SIGNAL LUX Mod 21.3 230V (T120) Silicon Leads
R1, R2 = RESISTENZE HEIZKÖRPER/HEATING ELEMENT	ø280 1.333x3=4000W 230V
CABLAGGIO ANSCHLUSSKABEL/POWER CORD	CAVO H05SJ-K Section 1.5 mmq
CABLAGGIO LAMPADE KABEL F. KONTROLLAMPE/CABLE F. IND. LIGHT	CAVO H05SJ-K Section 0.75 mmq